Pseudorandom Generators for Combinatorial Rectangles

Chi-Jen Lu
Institute of Information Science
Academia Sinica
Taipei, Taiwan, ROC.
Email: cjlu@iis.sinica.edu.tw

Area?



Rectangles of Dimension 2:



Combinatorial Rectangles $\mathcal{R}(m, d)$

- $\mathcal{R}(m, d)$ contains those

$$R_1 \times \cdots \times R_d = \{(x_1, \ldots, x_d) : x_1 \in R_1, \ldots, x_d \in R_d\},$$

where $\forall i, R_i \subseteq [m] = \{1, \ldots, m\}$.

- $vol(R) = P_{x \in [m]^d}[x \in R] = \prod_{i=1}^{d} \frac{|R_i|}{m}$, for $R \in \mathcal{R}(m, d)$.
- Need $\log m^d = d \log m$ bits to sample.
- Fewer random bits? Smaller sample space?
- $g : \{0,1\}^r \to [m]^d$ is an ε-PRG for $\mathcal{R}(m, d)$, if $\forall R \in \mathcal{R}(m, d)$,

$$|vol(R) - P_z[g(z) \in R]| \leq \varepsilon.$$

A Bad Sample Set:



A Good Sample Set:



RL vs. L

- $\mathbf{L} \subseteq \mathbf{SL} \subseteq \mathbf{RL}$.
- PRGs for **RL**, using $O(\log^2 n)$ bits [N 90].
- $\mathbf{RL} \subseteq \mathbf{SC}^2 = \mathbf{DSPACE,TIME}(\log^2, n^{O(1)})$ [N 92].
- $\mathbf{RL} \subseteq \mathbf{L}^{3/2} = \mathbf{DSPACE}(\log^{3/2} n)$ [SZ 95].
- $\mathbf{SL} \subseteq \mathbf{L}^{4/3} = \mathbf{DSPACE}(\log^{4/3} n)$ [ATWZ 97].

A Special Case: Rectangles

$$R = R_1 \times R_2 \times R_3 \times \cdots \times R_d.$$



With 2 branching program.

Other Related Problems

- Approximating generalized multivalued independent random variables.
- Approximate DNF counting DNF.

ε-PRGs for $\mathcal{R}(m, d)$

Number of Random Bits	$m, d, \frac{1}{\varepsilon} = n^{\Theta(1)}$	*Reference*
$O(\log d \log \frac{md}{\varepsilon}))$	$O(\log^2 n)$	[N 90]
$O(\log \frac{1}{\varepsilon} \log \frac{md}{\varepsilon}))$	$O(\log^2 n)$	[EGLNV 92]
$O(\log d \log \frac{d}{\varepsilon} + \log m)$	$O(\log^2 n)$	[INW 94]
$O(\log^2 \frac{1}{\varepsilon} + \log(md))$	$O(\log^2 n)$	[ASWZ 96]
$O(\log^{3/2} \frac{1}{\varepsilon} + \log(md))$	$O(\log^{3/2} n)$	[Lu 98]

- $d \downarrow \quad m \uparrow$ INW.

Saving Random Bits

- k-wise independence.
- Composing PRGs:

  $\boxed{l_1 \text{ bits}} \overset{g_1}{\to} \boxed{l_2 \text{ bits}} \overset{g_2}{\to} \boxed{l_3 \text{ bits}}$

k-wise Independent Space $\mathcal{H}_k(d,m)$

- $G \equiv \mathcal{H}_k(d,m) \subseteq [m]^d$.
- Each dim is uniform. Any k dim are independent.
- $\forall J = \{j_1, \ldots, j_k\} \subseteq [d]$ and $\forall B_{j_1}, \ldots, B_{j_k} \subseteq [m]$,

$$P_{y \in G}[\bigwedge_{j \in J} (y_j \in B_j)] = P_{y \in [m]^d}[\bigwedge_{j \in J} (y_j \in B_j)].$$

- Need $O(k \log \max(d,m))$ bits, instead of $d \log m$ bits.

G fools $\mathcal{R}(m, d)$

- Principle of Inclusion-Exclusion: For any $S \subseteq [m]^d$,



$$
\begin{aligned}
P_{y\in S}[y \in R] &= 1 \quad - P_{y\in S}[\bigvee_{j\in[d]} (y_j \in \overline{R}_j)] \\
&= 1 \quad - \sum_{j\in[d]} P_{y\in S}[y_j \in \overline{R}_j] \\
&\qquad + \sum_{J\subseteq[d],|J|=2} P_{y\in S}[\bigwedge_{j\in J} (y_j \in \overline{R}_j)] \\
&\qquad - \cdots \\
&\qquad + (-1)^k \sum_{J\subseteq[d],|J|=k} P_{y\in S}[\bigwedge_{j\in J} (y_j \in \overline{R}_j)] \\
&\qquad + \cdots
\end{aligned}
$$

- $P_{y \in [m]^d}[y \in R]$ and $P_{y \in G}[y \in R]$ agree up to the kth terms.



- $|P_{y \in [m]^d}[y \in R] - P_{y \in G}[y \in R]| \le \tau_k$.
- $k = \Omega(\log \frac{1}{\varepsilon})$ for error $\varepsilon \Rightarrow$
  $\Omega(\log \frac{1}{\varepsilon} \log \max(m, d))$ random bits.
- Smaller k?

Divide & Conquer

$$h : [d] \to [d'].\ \ g_h : G^{d'} \to [m]^d.$$

$$\begin{array}{ccccc}
\underbrace{R_1 \times R_2 \times R_3} & \times & \underbrace{R_4 \times R_5 \times R_6} & \times & \underbrace{R_7 \times R_8 \times R_d} \\
R_{h^{-1}(1)} & \times & R_{h^{-1}(2)} & \times & R_{h^{-1}(d')} \\
\uparrow & & \uparrow & & \uparrow \\
G & \times & G & \times & G
\end{array}$$

$$\begin{aligned}
& |vol(R) - P_{y \in G^{d'}}[g_h(y) \in R]| \\
\leq \ & |\prod_{j \in [d']} vol(R_{h^{-1}(j)}) - \prod_{j \in [d']} P_{z_j \in G}[z_j \in R_{h^{-1}(j)}]| \\
\leq \ & \sum_{j \in [d']} |vol(R_{h^{-1}(j)}) - P_{z_j \in G}[z_j \in R_{h^{-1}(j)}]| \\
\leq \ & \sum_{j \in [d']} \tau_k(h^{-1}(j)).
\end{aligned}$$

- Note: $\tau_j(I) = \sum_{J \subseteq I, |J| = j} \prod_{i \in J} \frac{|\overline{R}|}{m}$, for $I \subseteq [d]$.

Dividing Randomly

Let $d' = 2^{O(\frac{1}{k}\log\frac{1}{\varepsilon})}$ and $H \equiv \mathcal{H}_k(d, d')$.

Lemma: $|vol(R) - P_{h\in H, y\in G^{d'}}[g_h(y) \in R]| \le \varepsilon$.

Proof:

$$\begin{aligned}
& |vol(R) - E_{h\in H} P_{y\in G_h}[y \in R]| \\
\le\ & E_{h\in H} |vol(R) - P_{y\in G_h}[y \in R]| \\
\le\ & E_{h\in H} \sum_{j\in[d']} \tau_k(h^{-1}(j)) \\
=\ & \sum_{j\in[d']} E_{h\in H} \sum_{I\subseteq h^{-1}(j), |I|=k} \prod_{i\in I} \frac{|\overline{R}_i|}{m} \\
=\ & \sum_{j\in[d']} E_{h\in H} \sum_{I\subseteq [d], |I|=k} \delta[I \subseteq h^{-1}(j)] \prod_{i\in I} \frac{|\overline{R}_i|}{m} \\
=\ & \sum_{j\in[d']} \sum_{I\subseteq [d], |I|=k} P_{h\in H}[\forall i \in I, h(i) = j] \prod_{i\in I} \frac{|\overline{R}_i|}{m} \\
=\ & d'(\frac{1}{d'})^k \sum_{I\subseteq [d], |I|=k} \prod_{i\in I} \frac{|\overline{R}_i|}{m} \\
\le\ & \varepsilon^{\Omega(1)} \tau_k([d]).
\end{aligned}$$

- *Either* $\tau_k([d])$ is small,
  or both $vol(R)$ and $P_{h,y}[g_h(y) \in R]$ are small.

A Generator

$$g : H \times \mathbf{G}^{\mathbf{d}'} \to [m]^d, \text{ where } g(h,\cdot) = g_h(\cdot).$$

Composing Generators

Let $m' = |G|$. Then

$$R \in \mathcal{R}(m,d) \quad \Rightarrow \quad g_h^{-1}(R) \in \mathcal{R}(m',d').$$



Lemma: $f : \{0,1\}^r \to [m']^{d'}$ is an ε-PRG for $\mathcal{R}(m',d')$

$$\Rightarrow \; g(\cdot, f(\cdot)) \text{ is a } 2\varepsilon\text{-PRG for } \mathcal{R}(m,d).$$

Dimension Reduction

$\mathcal{R}(m,d) \Rightarrow \mathcal{R}(m',d')$.

- $m' = |G| = |\mathcal{H}_k(m,d)| = (m+d)^{O(k)}$.
- $d' = 2^{O(\frac{1}{k}\log\frac{1}{\varepsilon})}$.
- Cost$=\log_2|H| = O(k\log d)$.

INW-generator for $\mathcal{R}(m',d')$

Number of random bits

$$\begin{aligned}
&= O(\log m' + \log d'(\log\frac{1}{\varepsilon} + \log d'))\\
&= O(k\log(m+d) + \frac{1}{k}\log\frac{1}{\varepsilon}\log\frac{1}{\varepsilon})\\
&= O((\log^{1/2}\frac{1}{\varepsilon})(\log m + \log d + \log\frac{1}{\varepsilon})),
\end{aligned}$$

for $k = \log^{1/2}\frac{1}{\varepsilon}$.

Two More Reductions

Dimension Reduction I [ASWZ 96]:

$$\mathcal{R}(m,d) \Rightarrow \mathcal{R}(m_1,d_1): \quad \begin{aligned} d_1 &= (\tfrac{1}{\varepsilon})^{O(1)}, \\ m_1 &= (md)^{O(1)}, \\ c_1 &= O(\log d). \end{aligned}$$

Range Reduction:

Use extractors.

$$\mathcal{R}(m_1,d_1) \Rightarrow \mathcal{R}(m_2,d_2): \quad \begin{aligned} d_2 &= d_1, \\ m_2 &= (\tfrac{1}{\varepsilon})^{O(1)}, \\ c_2 &= O(\log \tfrac{md}{\varepsilon}). \end{aligned}$$

Theorem

$\exists$ ε-PRG for $\mathcal{R}(m,d)$ using $O(\log^{3/2}\frac{1}{\varepsilon} + \log m + \log d)$ random bits.

A Potential Improvement

Observation:

Okay if for small δ,

$$|P_{y\in[m]^d}[\bigwedge_{j\in J}(y_j \in \overline{R}_j)] - P_{y\in[m]^d}[\bigwedge_{j\in J}(y_j \in \overline{R}_j)]| \leq \delta.$$

Definition:

$\mathcal{R}(m,d,t)$: Rectangles from $\mathcal{R}(m,d)$ with at most t nontrivial ($\neq [m]$) dimensions.

Theorem:

$\exists$ ε-PRG for $\mathcal{R}(m,d,t)$ using $O(t + \log d + \log m + \log \frac{1}{\varepsilon})$ bits $\Rightarrow$
$\exists$ ε-PRG for $\mathcal{R}(m,d)$ using $O(\log d + \log m + \log \frac{1}{\varepsilon} \log\log \frac{1}{\varepsilon})$ bits.

Combinatorial Rectangles $\mathcal{B}(m, n, t)$

$\mathcal{B}(m, d, t)$ contains those $R = I_1 \times \cdots \times I_d$ s.t.

- $\forall i, I_i = \{a_i, a_i + 1, \ldots, a_i + b_i\}$, an interval.
- At most t nontrivial dimensions.

ε-PRGs for $\mathcal{B}(m, d, t)$

Number of Random Bits	*Reference*
$O(\log d + \log \frac{1}{\varepsilon} + t)$	[EGLNV 92]
$O(\log \log d + \log \frac{1}{\varepsilon} \log \frac{t}{\log 1/\varepsilon})$, for $t \geq \log 1/\varepsilon$	[CRS 94]
$O(\log \log d + \log \frac{1}{\varepsilon} \sqrt{\log \frac{t}{\log 1/\varepsilon}})$, for $t \geq \log 1/\varepsilon$	[Lu 98]